

tangent



Tangent HiFi AMP-200 Amplifier

Max power:	2 x 100W RMS
Frequency range +/- 3 dB:	10Hz-63.000 kHz
Distortion:	< 0.05 @ 1watt
Channel separation:	> 59dB
Tone control	Bass(+/-14dB), Treble(+/-14dB), balance
Signal / noise ratio:	> 90dB
Max power consumption	300 Watts
Speaker outputs:	High quality stereo binding posts
Analog audio outputs:	1 x stereo (line out)
Mains voltage:	220-240V / 50-60Hz
Dimensions (HxWxD)	115x 430 x 240mm
Analog audio inputs	Tuner, CD, DVD, AUX1, AUX2, AUX3, Phono
Analog audio outputs	Record out, preout, subwoofer out, Headphone out